## PRO - AV

NEW SOHO H-SERIES



### HIGH-END DIGITAL SIGNAGE SYSTEM



### Why choose ANGUSTOS Pro-AV?

We can provide you the best solution that suits your TVs, interactive screens, meeting room high-end projector, digital signage and videowall system. We do not just simply sell the equipments but also a smart solution that is just as well designed as it is functional. Solutions that guarantee and define our brand:

- ·Ease-of-use
- ·Design
- **Innovation**
- ·Reliability
- ·Ease-of-installation.

To help you find the exact solution you need, Angustos has an extensive product range that is possible to compose a solution for nearly every Pro AV application. Our highly skill solution teams are happy to help you to quickly find the best solution for your installation, saving you the time and effort and hassle for complex system.





# ANGUSTOS PRO AV APPLICATIONS

- Media Telecom Broadcast
- Education Training
- Manufacturing Quality Control
- Retail Advertising
- Meeting Room Conference
- Healthcare visual system
- Entertainment
- Government Control Room











## KVS0301K6P

# HDMI 4K SWITCH Model : KVS0301K6P

#### **FEATURES**

- HDMI 2.0 , HDCP 2.2 and EDID compliant
- Resolution 4K UHD@60Hz and 3D video.
- Manual switch button or IR remote
- HDR, HDR10, Dolby Vision and HLG
- Supports LPCM and DTS Digital,
- Dolby Digital (including DTS-HD and Dolby True HD)
- Ultra-low power consumption
- 5V USB to DC power cable included .



#### **PACKAGE**

HDMI Swich unit x 1

USB Power Cable x 1

Remote Control x 1











#### **SPECIFICATION**

Operating Temperature	-10° to 60°C
Operating Humidity	5 to 90%RH
Video Input Connectors	3 x HDMI
Video Output Connectors	1 x HDMI
Video Bandwidth	18 Gbps
<b>Audio Format Support</b>	DTS-HD, Dolby 5.1, DTS 5.1
	Dolby True HD, PCM 5.1/7.1

Colour Depth:	8-bit (4K60Hz), 4:4:4
Weight	60g
Standard	HDMI 2.0/ HDCP 2.2
Max Resolution	3840x2160 @ 60Hz
Power Supply/Consumption	5 V/1A - 2W (Max)
Dimension (L x W x H)	87 x 59 x 19
ESD / Impendance	$\pm 4$ - 8kV $/$ 100 $\Omega$

### CONNECTION DIAGRAM



