

RAPTOR-1KRT/RAPTOR-2KRT/RAPTOR-3KRT

Overview

The high quality Online Double-Conversion UPS that offers the ideal power protection. Designed for office and data center applications, the RAPTOR Series adopts double-conversion topology to provide seamless Pure Sine Wave output. The UPSs are compatible with generators to prolong power continuity.

The products also adopt ECO Mode to help save on energy costs, Smart Battery Management (SBM) to extend battery life, and multifunction LCD readout to display precise information. The power management software allows users to easily control and monitor the UPS system.



Features

- Rack/Tower convertible design
- Online double conversion with full digital control
- Wide input voltage range: 110~300Vac
- Input power factor 0.99 with PFC
- Selectable output voltage: 208/220/230/240Vac
- Smart charger design for optimized battery performance
- Maximum charging current can be expanded to 12A (Long run unit)
- Emergency power off function (EPO)
- ECO mode operation for energy saving
- Generator compatible
- Hot-Swappable battery design
- Cold start
- Intelligent fan speed regulation
- Load segment settable (Optional)
- Versatile LCD human-computer interface
- Multiple communication interface: RS232 (USB/EPO/Relay card /SNMP card optional)
- Multiple protection function: short-circuit, over-load, overheat, battery overcharge and overdischarge, output low voltage and fan fault alarm


Application

Raptor 1~3kVA, Rack/Tower convertible models application areas

- Data Network: Mid - range Servers (Windows and Linux), Wi-Fi Applications & Data networks
- Small Data Center Rooms
- Voice Networks: Cellular Sites, Voice Over IP (VOIP), Very small Aperture Terminals (VSAT) PBX And IT-enabled PBX Automation industries
- Process Automation Equipment: Programmable Logic Controllers (PLS) and Cash Machines (ATM)

Advanced protection for :

- Infrastructure
- Industrial and Medical IT
- Networking
- Storage
- Telecom



Online (Double Conversion) UPS Topology



Extended Battery Module (EBM)



Zero Transfer Time



Remote Management Capability



Smart Battery Management



Energy Saving Technology

Angustos

Angustos was founded in 2000 and is now regarded as one of the foremost manufacturers of Uninterruptible Power Supply, IT equipments,...

For more than 20 years our customers have been convinced by our core competencies in extending, switching and distributing standardised computer signals.

We are committed to established international standards. We can provide customers with complete Datacenter & Power solutions as well as OEM/ODM services. We can cover even from medium to small business, factory & industrial, military & government, home office & personal use.

SPECIFICATION



Model Name	RAPTOR-1KRT		RAPTOR-2KRT		RAPTOR-3KRT	
Power Rating	1 kVA / 0.9 kW		2 kVA / 1.8 kW		3 kVA / 2.7 kW	
GENERAL						
UPS Topology	Online Double Conversion					
ECO Technology	Online ECO Mode Efficiency ≥ 96%					
Generator Compatibility	Yes					
INPUT						
Nominal Voltage	208/220/230/240Vac					
Input Voltage Range	110~300Vac (176~264Vac @ 100% load)					
Power Factor	≥0.99					
Frequency Range	40~70Hz (50/60Hz, 50±10Hz, 60±10Hz)					
Frequency Detection	Auto-sensing					
Overload Capability	< 105%: Continuous; 105~125%: 1 minute; 125~150%: 15 seconds					
Input Connector Type	IEC C14		IEC C20			
OUTPUT						
Voltage	208/220/230/240Vac					
Voltage Regulation	±1%					
Output Voltage Setting	Configurable					
Output Frequency	(50 ± 0.1%, 60 ± 0.1%)Hz					
Power Factor	0.9					
Harmonic distortion	THDv < 3% Linear load, THDv < 5% Non linear load					
Transfer time	AC mode to Battery mode : 0ms, Inverter to Bypass : 4ms (typical)					
Efficiency AC-AC	91%		Up to 94%			
Output Connect Type	8 x IEC C13		8 x IEC C13		8 x IEC C13 + 1 IEC C19	
BATTERY						
Voltage	24VDC		48VDC		72VDC	
Runtime@50% Load(min)	16		15		15	
Runtime@100%Load(min)	6		6		6	
Typical Recharging Time	4 hours (To 90% of full capacity)					
Charging current (Max.)	1A					
INDICATORS						
LED display	Battery mode, Line mode, Bypass mode, ECO mode, Battery low voltage, Overload & UPS fault					
LCD display	Input frequency, Input voltage, Output frequency, Output voltage, Load percentage, Battery voltage, Inner temperature & Remaining battery backup time					
Alarm	Battery mode : beeping every 4 seconds; Battery low : beeping every second; Overload : beeping twice every second; Fault : continuously beeping					
PHYSICAL & STANDARDS & ENVIRONMENT						
Dimension(WxDxH)/Weight	440×325×86.5mm/11.3kg		440×460×86.5mm/19.5kg		440×600×86.5mm/26kg	
SAFETY	IEC/EN 62040-1, IEC/EN 62477-1					
EMC	IEC/EN 62040-2 (IEC 61000-4-2, IEC 61000-4-3, IEC 61000-4-4, IEC 61000-4-5, IEC 61000-4-6, IEC 61000-4-8, IEC 61000-4-11, IEC 61000-2-2)					
Environment	Operating temperature : 0°C - 40°C; Storage temperature : -25°C~55°C; Humidity range : 20~95%RH @ 0~40°C (Non condensing) Altitude : < 1500m, derating required when >1500m; Noise level < 50dB at 1 Meter					

1. When output voltage is 208Vac, need to derate to 80% of the unit capacity
2. Specifications are subject to change without prior notice
3. Data above are typical values for reference only, not as a basis for engineering design